



Notes:

1. Connecting customer generation equipment to the Benton PUD (BPUD) distribution system requires completion of a Net Metering Application and signing of a Net Metering Interconnection Agreement.
2. This standard represents a typical arrangement for a net metering installation. The details shown are not intended to depict Washington State Department of Labor and Industries (L&I) requirements. L&I approval of installation is required prior to customer receiving approval from BPUD for final interconnection of generator to the BPUD distribution system. Customer shall provide BPUD with a copy of the documentation of L&I approval.
3. Customer's must provide a one-line electrical schematic drawing to BPUD which is specific to the proposed installation.
4. BPUD does not require a utility disconnect switch for customer generation equipment utilizing Underwriter's Laboratory (UL) 1741 listed inverter equipment. Contact the BPUD engineering department for review and approval of other interconnection methods.
5. Upon receiving L&I approval, BPUD will complete a field inspection of the customer's net metering installation. Approved installations will be documented by BPUD's completion of a Generating Facility Certificate of Completion. This certificate represents the customer's authorization to energize their generation equipment and interconnect their net metering installation to the BPUD distribution system.
6. AC production meter base shall be labeled, "CUSTOMER GENERATOR, PRODUCTION METER", with engraved phenolic placards; 3/8" white capitalized lettering on a red background.
7. Main electric service (Net Meter) meter base shall be labeled "NET METER, CUSTOMER GENERATOR CONNECTED TO THIS SERVICE", with engraved phenolic placards; 3/8" white capitalized lettering on a red background.
8. When the production meter is not within line of sight of the net meter, an engraved placard showing both meter locations shall be installed next to the production meter.



TITLE:

Customer Generator Net Metering Installation

REV BY:	TMG	SHT.	
REV DATE:	8/29/2020		1 of 1
REV NO:	3	DIR. ENG.	DATE: 9/21/20
DWG. NO.			

Q-8A

DRAWN BY: SWT

DRAW DATE: 06/02/10